



Model : BZ-AIR-01

- Interactive with Other Z-wave Device
- Adopt Z-Wave 500 Module
- Compact design and easy installation
- Extremely Low Power Consumption
- Long Battery Life

TECHNICAL SPECIFICATIONS

Rated Voltage	3.0V by CR123
RF Distance (Z-Wave)	Min 40M indoor, 100M outdoor line of sight
RF Frequency	921.4MHz Transceiver
Chip	Z-Wave 500 Series Module
Battery	CR123A
Sensitivity	Wall Mount : 8M Ceiling Mount : Height 4M Radius Distance 6M
Body Dimension	Ø 45.5 X 49.3 mm
Body Weight	120g
Body Dimension	Ø 71.2 X 10.9 mm
Bracket Weight	30g
IP Classification	Indoor Use
Operation Temperature	0 ~ 40°C
Operation Humidity	85%RH max